



# BDJ BUDGET EASY SET



**BDJ Budget EasySet** is a set of products including BDJ Budget. The blowing machine is paired with a dedicated drill/drive unit-spare battery included and a customised small stainless steel tripod. The blowing unit is designed **to build the last sections of the FTTH network**. Delivered with special bushings facilitating blowing fiber optic cables from  $\varnothing$  0.5mm diameter.

## Blowing range:

- **Cable diameter**  $\varnothing$  0,5 mm - 6 mm
- **Duct diameter**  $\varnothing$  5, 7, 10, 12, 14, 16 mm

## Accessories included inside the set:

- micro duct cutter,
- set of bushings and micro duct connectors,
- set of gaskets,
- tools,
- spare wheels with removable rubber bands,
- air hose.



# TECHNICAL DATA

<b>MICRO CABLE DIAMETER</b>	0,5 mm – 6 mm
<b>MICRO TUBE DIAMETER</b>	5, 7, 10 mm
<b>BLOWING DISTANCE / MAX</b>	700 m
<b>BLOWING SPEED / MAX</b>	60 m/min
<b>WORK PRESSURE / MAX</b>	15 bar
<b>DIMENSIONS OF THE UNIT (L X W X H)</b>	260 x 100 x 140mm weight approx. 2kg
<b>DIMENSIONS OF THE TRANSPORT TRUNK</b>	465 x 400 x 155mm weight approx. 8kg
<b>AVAILABLE ACCESSORIES</b>	<ul style="list-style-type: none"><li>• micro duct cutter</li><li>• set of bushings and micro duct connectors</li><li>• set of gaskets</li><li>• tools</li><li>• spare wheels with removable rubber bands</li><li>• air hose</li></ul>
<b>REQUIRED COMPRESSOR'S EFFICIENCY</b>	<ul style="list-style-type: none"><li>• micro ducts up till 8 mm-0,8m<sup>3</sup>/min</li><li>• micro ducts between 8-12 mm-1,0m<sup>3</sup>/min</li><li>• micro ducts between 12-15 mm - 1,5m<sup>3</sup>/min</li></ul>

**REQUIRED COMPRESSOR: KAESER M17A**